

Timelapse mode

| Time interval | Est. TLC130 battery life (days) | Est. ATH2000 battery life (days) | Est. total battery life (days) |
|---------------|---------------------------------|----------------------------------|--------------------------------|
| ASAP | 0.3 | 1.1 | 1.4 |
| 1 sec | 0.3 | 1.1 | 1.4 |
| 2 sec | 0.6 | 2.3 | 2.9 |
| 5 sec | 1.1 | 4.5 | 5.6 |
| 10 sec | 1.4 | 5.4 | 6.8 |
| 20 sec | 1.7 | 6.6 | 8.3 |
| 30 sec | 2.8 | 11.2 | 14 |
| 1 min | 4.1 | 16.5 | 20.6 |
| 5 min | 11.1 | 44.5 | 55.6 |
| 10 min | 12.8 | 51.1 | 63.9 |
| 1 hr | 14.9 | 59.4 | 74.3 |
| 4 hr | 15.5 | 61.9 | 77.4 |
| 24 hr | 16.2 | 64.8 | 81 |

Step video mode

| Burst Length | Time interval | Est. TLC130 battery life (days) | Est. ATH2000 battery life (days) | Est. total battery life (days) |
|---------------|---------------|---------------------------------|----------------------------------|--------------------------------|
| 3 sec | 30 sec | 0.2 | 0.9 | 1.1 |
| | 1 min | 1.0 | 4.0 | 5 |
| | 3 min | 1.6 | 6.2 | 7.8 |
| | 5 min | 4.0 | 15.9 | 19.9 |
| | 10 min | 6.6 | 26.4 | 33 |
| 5 sec | 1 min | 0.8 | 3.0 | 3.8 |
| | 3 min | 2.2 | 8.7 | 10.9 |
| | 5 min | 3.2 | 13.0 | 16.2 |
| | 10 min | 5.7 | 22.7 | 28.4 |
| 10 sec | 3 min | 1.5 | 5.9 | 7.4 |
| | 5 min | 1.9 | 7.5 | 9.4 |
| | 10 min | 4.1 | 16.6 | 20.7 |

- Battery life may vary based on environmental conditions, temperature, and many other factors; actual results will vary.
- The numbers above shown in the following tables require to charge a fully battery in TLC130 and install new batteries in ATH2000.
- Rechargeable batteries are not recommended as the lower voltage they produce may vary performance.

